

KombiSIGN 40 / ClassicLOOK

TwinFLASH Classic 24VDC GN



| MECHANICAL DATA | | |
|-----------------------------|---------------|--|
| Height | 59 mm | |
| Diameter | 40 mm | |
| Materials | PC | |
| Dome colour | Green | |
| Protection category | IP66 IP69K | |
| Working temperature minimum | -30°C | |
| Working temperature maximum | +60°C | |
| Weight with packaging | 40 g | |
| Product weight | 30 g | |

| ELECTRICAL DATA | |
|-----------------------------|--------------------|
| Operating voltage | 24V |
| Operating voltage type | DC |
| Operating voltage tolerance | +/- 10% |
| Rated operational voltage | 24 VDC |
| Rated operational current | 65 mA |
| Rated inrush current | 500 mA |
| Protection class | Protection class 3 |
| Pollution degree | 3 |
| Request to external PSU | SELV/PELV |

| OPTICAL DATA | |
|----------------------|---------------------------|
| Light source | LED |
| Light colour | Green |
| Optical signal image | EVS Flash TwinFlash |
| Flash frequency | 1 Hz |
| Service life optical | 50,000 h maximum |

| APPROVAL DATA | | |
|------------------------------|---------|--|
| Conforms with CE | Yes | |
| Conforms with RoHS directive | Yes | |
| WEEE | Yes | |
| Conforms with ATEX-directive | No | |
| Conforms with CCC | No | |
| Conforms with UL | cULus | |
| UL Type Rating | Type 12 | |
| Conforms with FCC | No | |

For additional installation and mounting information, refer to the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.



KombiSIGN 40 / ClassicLOOK

TwinFLASH Classic 24VDC GN

| Conforms with IC | No |
|-------------------------------|-----------------------|
| EAC certificate available | Yes |
| Conforms with UKCA (Importer) | Yes (WERMA (UK) Ltd.) |
| Conforms with CMIM | No |
| Conforms with AS-I | No |
| ICAO Certification | No |
| Conforms with DNV | No |
| Conforms with RoHS CN | No |
| Conforms with VdS | No |
| MTTF-value [years] | 1323 |

BY OS Ø40

For additional installation and mounting information, refer to the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.