

## DIFFERENTIAL CURRENT CIRCUIT BREAKER AC 2P 16A 30mA SCHELINGER



CODE: A03-K7-2-16-030

EAN: 5900280965431

| Electrical data           |                        |
|---------------------------|------------------------|
| Nominal voltage           | 230/240V~ 50/60Hz      |
| Installation Data         |                        |
| Height                    | 68mm                   |
| Length                    | 83mm                   |
| Width                     | 36mm                   |
| Certificates and markings |                        |
| Degree of protection      | IP20                   |
| Packaging                 |                        |
| Carton                    | 100                    |
| Other                     |                        |
| Characteristic            | AC                     |
| Contractual fault current | I <sub>cn</sub> : 10kA |
| Differential current      | 30mA                   |
| Installation              | DIN/TH rail 35mm       |
| Insulation voltage rating | U <sub>i</sub> : 415V  |
| Number of modules         | 2                      |
| Operating temperature     | -25°C /+40°C           |
| Surge voltage             | U <sub>imp</sub> : 4kV |
| Rated current             | I <sub>n</sub> : 16A   |
| Brand                     | Schelinger             |